

B.Tech. VIII Semester (Main/Back) Examination, 2014

Electrical Engineering

Electric Drives and Their Control

(Common with 8E X2)

Time: 3 Hours

Maximum Marks: 80

Min. Passing Marks: 24

Instructions to Candidates:

Attempt any five questions, selecting one question from each unit. All questions carry equal marks. (Schematic diagrams must be shown wherever necessary. Any data you feel missing suitably be assumed and stated clearly. Units of quantities used/calculated must be stated clearly.)

Unit-I

- Q.1 (a) Explain load equalization in drives with necessary diagrams and derivations. [8]
- (b) A motor equipped with a flywheel is to supply a load torque of 1000 N-m for 10 sec. followed by a light load period of 200 N-m long enough for the flywheel to regain its steady state speed. It is desired to limit the motor torque to 700 N-m. What should be the moment of inertia of flywheel? Motor has an inertia of 10 Kg - m². Its no load speed is 500 rpm and the slip at a torque of 500 N-m is 5%. Assume speed - torque characteristics of motor to be a straight line in the region of interest. [8]

OR

- Q.1 (a) Enumerate the various nature and classification of load torques. [8]
- (b) Explain what do you understand by the steady state stability? What is the main assumption? [8]

Unit-II

- Q.2 (a) State and explain the important features of various braking methods of d.c. motors. [8]
- (b) A 220 V, 200A, 800 rpm dc separately excited motor has an armature resistance of 0.06Ω. The motor armature is fed from a variable voltage source with an internal resistance of 0.04Ω. Calculate internal voltage of the variable voltage when the motor is operating in regenerative braking at 80% of the rated motor torque and 600 rpm. [8]

OR

- Q.2 (a) Explain the various methods of speed control for d.c. motors. [8]
(b) A 200 V, 10.5 A, 2000 rpm shunt motor has the armature and field resistances of 0.5 and 400Ω respectively. It drives a load whose torque is constant at rated motor torque. Calculate speed if source voltage drops to 175 V. [8]

Unit-III

- Q.3 (a) Explain the various starting methods for three phase induction motors. [8]
(b) A 400 V, star connected, 3 phase, 6 pole, 50 Hz induction motor has following parameters referred to stator : $R_s = R_r' = 1\Omega$ $X_s = X_r' = 2\Omega$. For regenerative braking operation of this motor determine over hauling torque it can hold and range of speed for safe operation. [8]

OR

- Q.3 (a) Discuss the voltage source inverter fed induction motor drive operated in stepped wave inverter mode. [8]
(b) Discuss the A.C. dynamic braking with two lead connection for Induction motor drives. [8]

Unit-IV

- Q.4 (a) Explain the slip power recovery scheme with static scherbius drive. [8]
(b) Explain the static rotor resistance control for I.M. drives. [8]

OR

- Q.4 (a) Explain static Kramer drive for I.M. drives with necessary derivation and sketches. [8]
(b) Discuss the current source inverter control for I.M. drives. [8]

Unit-V

- Q.5 (a) Discuss the operation of VSI fed self controlled synchronous motor drives. [8]
(b) Explain the braking of synchronous motor with VSI. Draw the speed torque characteristics for regenerative braking. [8]

OR

- Q.5 (a) Explain the control of synchronous motor with CSI. [8]
(b) Explain the dynamic braking of synchronous motor with VSI. [8]